

| | | |
|-------------|---|--|
| Part number | LVDS-FI-X30HL-A1014H-2X20P-400-G17 | |
| Type | LVDS cable between G170ETN01.0 and SECO SBC A62 | |
| Length | 400 mm | |
| Connector 1 | FI-X30HL | |
| Connector 2 | A1014H-2X20P | |

| Connector 1 | |
|-------------|----------|
| FI-X30HL | |
| 1 | OddDA0- |
| 2 | OddDA0+ |
| 3 | OddDA1- |
| 4 | OddDA1+ |
| 5 | OddDA2- |
| 6 | OddDA2+ |
| 7 | GND |
| 8 | OddClk- |
| 9 | OddClk+ |
| 10 | OddDA3- |
| 11 | OddDA3+ |
| 12 | EvenDA0- |
| 13 | EvenDA0+ |
| 14 | GND |
| 15 | EvenDA1- |
| 16 | EvenDA1+ |
| 17 | GND |
| 18 | EvenDA2- |
| 19 | EvenDA2+ |
| 20 | EvenClk- |
| 21 | EvenClk+ |
| 22 | EvenDA3- |
| 23 | EvenDA3+ |
| 24 | GND |
| 25 | |
| 26 | |
| 27 | |
| 28 | |
| 29 | Vcc |
| 30 | Vcc |

| Connector 2 | |
|--------------|----------|
| A1014H-2X20P | |
| 1 | |
| 2 | |
| 3 | Vcc |
| 4 | |
| 5 | Vcc |
| 6 | |
| 7 | EvenDA0- |
| 8 | OddDA0- |
| 9 | EvenDA0+ |
| 10 | OddDA0+ |
| 11 | GND |
| 12 | |
| 13 | EvenDA1- |
| 14 | OddDA1- |
| 15 | EvenDA1+ |
| 16 | OddDA1+ |
| 17 | GND |
| 18 | |
| 19 | EvenDA2- |
| 20 | OddDA2- |
| 21 | EvenDA2+ |
| 22 | OddDA2+ |
| 23 | |
| 24 | GND |
| 25 | EvenDA3- |
| 26 | OddDA3- |
| 27 | EvenDA3+ |
| 28 | OddDA3+ |
| 29 | |
| 30 | GND |
| 31 | EvenClk- |
| 32 | OddClk- |
| 33 | EvenClk+ |
| 34 | OddClk+ |
| 35 | |
| 36 | |
| 37 | |
| 38 | |
| 39 | |
| 40 | |

TOP VIEW ON CONNECTOR

